

External Battery Box

An external battery box eases meter battery change.
It could also be used for communication junctions or special circuits.



**Model 1000-0-R4-
CANTEX-3**

Ordering Instructions

Model 1800-0-R13-CANTEX-3-R

R for Reversed mount
Box position in clock time

Number of Jaws

4 for 2S

5 for 12S

6 for 4S

7 for 14, 15, 16S

8 for 8S

13 for 6, 8, 9, 10S

Meter socket type

1000 for Ring style

1800 for Ringless style

The final "R" indicates reversed mounting of the battery box, placing the screws to the wall as shown in the photo of the 1800-R13-CANTEX-12-R, above right.




**Model 1800-R13-
CANTEX-12-R**

Adapter Specifications

Modified version of the UL Listed 1000-0-R4.
Patented jaw for 200 Amp continuous duty.
CANTEX Weatherproof 2 X 2 X 4 inch non-metallic box.
Marwell 4-Bolt 1.5" x 2" non-metallic coupler.
Screw cap seals (2) included to seal the cover.

For information email david@marwellcorp.com



World's leading manufacturer of UL Listed meter socket adapters

MARWELL CORPORATION



PO BOX 139 * MENTONE, CA 92359 * 909-794-4192 * FAX 909-794-0250